

MODEL	P/U ROLLER	SEP PAD	FUSER	Maint. Kit	TRANSFER	P/U ASSY	Delivery Assembly	TONER
II, III	RA1-3851	RF1-1145	RG1-0939R	33449-69007R	NLA	NLA		92295A
IIIP, IIIP	RA1-7573(T1) RA1-7824(T2) RA1-7674(T2)	RG1-1912	RG1-1788E	33481-69007E		RG1-1792		92275A
IIISi, 4Si	RF5-0041 RF5-0081(DUP)	RF5-0041	RG5-0046E	C2062-67901E	RG5-0141	RG5-0027	RG5-0381E (Offset)	92291A
4	RB1-2127(T1) RB1-2126(T2) RB1-2632(T3)	RF5-0343	RG5-0454E	C2001-67912E	RF5-0349	RG5-0451	RG5-0456-KIT	92298A
4+	RB1-2127(T1) RB1-3477(T2) RB1-2632(T3)	RF5-0343	RG5-0879E	C2037-69010E	RF5-0349	RG5-0877	RG5-0886	92298A
4L, 4P	RB1-3029	RF5-0343	RG5-0676	C2003-69010	RF5-0596	RG5-0668		92274A
4V	RB1-1411(T1) RB1-1386(T2)	RF5-0302 (T1)	RG5-1557E	C3141-69010E	RG5-1410	RG5-2248	RG5-0198	C3900A
5	RB1-2205(T1) RB1-7911(T2) RB1-7983(T3)	RF5-0343	RG5-0879E	C3916-69001E	RF5-0349	RG5-2195	RG5-2189E	92298A
CLJ 5	07BA-4062KC		C3969-67901	N/A				C3105A(B)
5L	RB2-1634	RB2-6221	RG5-1964	H3971-60001	RF5-1534	RG5-1951	RG5-2012	C3906A
5P	RB1-2205(T1) RB1-6332(T2)	RF5-0343	RG5-1700E	H3973-69001E	RF5-0596	RG9-1082(T1)	RG5-0683	C3903A
5Si	RB1-6730(T1) RF5-1835 (T2&3)	RF5-1455 RF5-1834 Feed/Sep Roll	RG5-4447E	C3971-69002E	RF5-1412	RG5-1880(T1) RG5-1852(PIU)	RG5-1874E	C3909A
6L	RB2-1634(T1) RY7-5077 HB1-3035 (Doc Scan)	RB2-6221	RG5-3459	H3972-60001	RF5-1534	RG5-3486(T1)	RG5-3474	C3906A
6P	RB1-2205(T1) RB1-6332(T2)	RF5-0343	RG5-4110E	H3966-69010E	RF5-0596	RG5-2790(T1) RG5-2796(T2)	RG5-0683	C3903A
1000	RL1-0303	RF0-1014	RG9-1493		RG9-1483	RG0-1085	RG0-1010	C7115A

MODEL	P/U ROLLER	SEP PAD	FUSER	Maint. Kit	TRANSFER	P/U ASSY	Delivery Assembly	TONER
1005	RL1-0303	RF0-1014	RG9-1494 (220V)		RG9-1483	RG0-1003	RG0-1010	C7115A C7115X
1010/1012/1015	RL1-0266	RM1-0648	RM1-0660	N/A	RM1-0658	RM1-0641	RM1-0659	Q2612A
1020	RL1-0266	RM1-0648	RM1-2086		RM1-2093	RM1-2091	RM1-0659	Q2612A
1022	RL1-0266	RM1-2048	RM1-2049		RM1-2062	RM1-2043		Q2612A
1100	RB2-4026	RF5-2886	RG5-4589	H3965-60001	RG5-4657	RG5-4581	RG5-4593	C4092A
1150	RL1-0303	RF0-1014	RM1-0715	LP-MK1300	RM1-0550	RM1-0531	RM1-0556	Q2624A
1160	RL1-0540	RM1-1298 (T2)	RM1-1289	LP-MK1320	RM1-1471		RL1-0527	Q5949A
1200	RL1-0303	RF0-1014	RG9-1493	LP-MK1200	RG9-1483	RG0-1085	RG0-1010	C7115A
1300	RL1-0303	RF0-1014	RM1-0715	LP-MK1300	RM1-0550	RM1-0531	RM1-0556	Q2613A
1320	RL1-0540	RM1-1298 (T2)	RM1-1289	LP-MK1320	RM1-1471		RL1-0527	Q5949A/X
CLJ 1500	RB3-0160(T1) RB3-0161(T2)	RF5-4012(T1) RF5-4258 (500S) RC1-0954 (250S)	RG5-6903	N/A	RF5-4040	RG5-6952(T1)	RG5-6897-Upper RG5-6936-Lower	C9700A(B) C9701A(C) C9702A(Y) C9703A(M)
CLJ 1600	RC1-5440	RM1-1922	RM1-1820					Q6000A (B) Q6001A (C) Q6002A (Y) Q6003A (M)
P2015	RL1-1525 (T1) RL1-0540 (T2)	RL1-1524 (T1) RM1-1298 (T2) (In tray)	RM1-4247		RM1-4279			Q7553A or X
2100	RB2-2900(T1) RB2-2891(T2)	RB2-6348(T1) RB2-6349(T2&3)	RG5-4132E	H3974-60001E	RG5-4164	RG5-4128(T1) RG5-4127(T2)	RF5-2604	C4096A
2200	RB2-2900(T1) RB2-6304(T2)	RF5-3272(T1) RB2-6349(T2&3)	RG5-5559E	H3978-60001E	RG5-5581	RG5-4128(T1) C7058-67907(T2)	C7058-67905	C4096A
2300	RC1-0945(T1) RB2-6304(T2&3)	RC1-0939 (T1) RC1-0954 (250T) RF5-4258 (500T)	RM1-0354	U6180-60001	RM1-0343	RM1-0332(T2)	RM1-0371	Q2610A

MODEL	P/U ROLLER	SEP PAD	FUSER	Maint. Kit	TRANSFER	P/U ASSY	Delivery Assembly	TONER
2400 / 2420 / 2430	RL1-0568(T1) "D" RL1-0542 (T2 & 3)	RC1-0939 (T1) FM2-6009 (T2)-250 RB2-6474 (T3)-500	RM1-1535	H3980-6001	RM1-1508	RM1-1484 (T1) RM1-1481 (T2)	RL1-0580	Q6511A / X
CLJ 2500	RB3-0160(T1) RB3-0161(T2)	RF5-4012(T1) RF5-4258 (500S) RC1-0954 (250S)	RG5-6903	N/A	RF5-4040	RG5-6952(T1)	RG5-6897-Upper RG5-6936-Lower	C9700A(B) C9701A(C) C9702A(Y) C9703A(M)
CLJ 2550	RB3-0160 (T1) RB3-0161 (T2)	RF5-4012(T1)	RG5-7572	N/A	RF5-4067	RG5-6952(T1)	RG5-6897 - Upper RG5-7595 - Lower	Q3960A(B) Q3971A(C) Q3972A(Y) Q3973A(M)
CLJ 2600	RC1-5440	RM1-1922	RM1-1820	N/A	RM1-1885 Belt			Q6000A(B) Q6001A(C) Q6002A(Y) Q6003A(M)
CLJ2820 / 2840	RB3-0160(T1)	RF5-4012 (T1) RF5-4258 (T2)	RG5-7602	N/A	RF5-4067	RG5-6952 (T1)	RG5-7637 RG5-7595	Q3960A(B) Q3961A(C) Q3962A(Y) Q3963A(M)
CLJ 3000	RM1-2702	RM1-2699 (T1) RM1-2709 (T2)	RM1-2665	N/A	RM1-2759 Belt	RM1-2774	RM1-2722 (Duplex)	Q7560A(B) Q7561A(C) Q7562A(Y) Q7563A(M)
P3005	RL1-0568 (T1) RL1-1370 (T2)	RC1-0939 (T1) RM1-1298 (T2) (In tray)	RM1-3740		RM1-1508	RM1-3762 (T2)		Q7551A or X
3015 mfp	RL1-0266 (D Roller)	RM1-0648 RM1-0890 (Scan Assy)	RM1-0865	N/A	RM1-0658	RM1-0864	RM1-0859	Q2612A
3020 / 3030 mfp	RL1-0266 (D Roller)	RM1-0648 C7309-60076 (ADF)	RM1-0865	N/A	RM1-0658	RM1-0864 C7309-60049 (ADF)	RM1-0859	Q2612A
3100 / 3150	RB2-1634 RG5-4772 (ADF)	RY7-5077 HB1-3035 (Doc Scan)	RG5-4678	H3975-60001	RF5-1534	RG5-3486(T1)	RG5-3474	C3906A
3200	RB2-4026(T1)	RF5-2886	RG5-4589	H3965-60001	RG5-4657	RG5-4581(Feed)	RG5-4593	C4092A

MODEL	P/U ROLLER	SEP PAD	FUSER	Maint. Kit	TRANSFER	P/U ASSY	Delivery Assembly	TONER
	RG5-5401(ADF)	RG5-5404(ADF) HB1-3035(Doc Scan)				RG5-5399(ADF)		
3300 Series	RL1-0303 (D Roll)	RF0-1014	RG9-1493	N/A	RG9-1483	RG0-1120	RG0-1010	C7115A
	C7309-60091 ADF	C7309-60009 ADF						C7115X
3380 mfp	RL1-0303 (D Roller)	RF0-1014	RM1-2075	N/A	RM1-0550	RM1-0838 (P/U) C7309-60049 (ADF)	RM1-0556	C7115A C7115X
CLJ 3500 / 3550	RC1-1535 (T1)	RC1-0939 (T1)	Q3655A (Kit)	N/A	Q3658A (Kit)	RM1-0765	RM1-0744 (FD)	Q2670A(B) Q2671A(C) Q2672A(Y) Q2673A(M)
	RM1-0731 (T2)	RM1-0739 (T2)			RM1-0740			
		RC1-0954 (250S)						
		RM1-0827 (500S)						
CLJ 3600	RM1-2741 (T1)	RM1-2699 (T1)	RM1-2665	N/A	RM1-2759 (Belt)	RM1-2755 (T1&2)	RM1-2722 (Duplex)	Q6470A (B) Q6471A (C) Q6472A (Y) Q6473Q (M)
	RM1-2702 (T2)	RM1-2709 (T2)						
	RM1-2727 (T3)	RM1-2733 (T3)						
CLJ 3700	RC1-1535 (T1)	RC1-0939 (T1)	Q3655A (Kit)	N/A	Q3658A (Kit)	RM1-0741		Q2670A(B) Q2681A(C) Q2682A(Y) Q2683A(M)
	RM1-0731 (T2&3)	RM1-0739 (T1 with holder)						
		RC1-0954 (T2) (250S)						
		RM1-0827 (T3) (500S)						
CLJ 3800	RM1-2741 (T1) P/U	RM1-2699 (T1)	RM1-2665	N/A	RM1-2759 (Belt)	RM1-2755 (T1&2)	RM1-2722 (Duplex)	Q6470A (B) Q7581A (C) Q7582A (Y) Q7583A (M)
	RM1-2702 (T2) P/U	RM1-2709 (T2)						
	RM1-2727 (T3) P/U	RM1-2733 (T3)						
4000 / 4050	RG9-1529(T1)	RG5-5281	RG5-2661E	C4118-67902E	RG5-4283	RG5-2655(T1) RF5-2484(T2) RG5-2672(500T)	RG5-2648	C4127A C4127X
	FB4-9817(T2&3)x4 "D"	RF5-1885 Feed/Sep Roll						
4100	RG9-1529(T1)	RF5-3086	RG5-5063E	C8057-67901E	RG5-5295	RG5-5084(T1) RG5-5277(T2) RG5-5293(500)	RG5-5094	C8061A C8061X
	RB1-8957x4 "D"	RF5-3114 (T2) Feed/Sep Roll						
4101 mfp	RG9-1529(T1)	RF5-3086	RG5-5063E	C8057-67901	RG5-5295	RG5-5084(T1) RG5-5277(T2) RG5-5293(500)	RG5-5094	C8061A C8061X
	RB1-8957x4 "D"	RF5-3114 (T2) Feed/Sep Roll						
	RB2-8769 (ADF)	RF5-3808 (ADF)						
4200	RL1-0019(T1) "D"	RL1-0007(T1)	RM1-0013E	Q2429-67902E	RM1-0699	RM1-0034(T1)	RM1-0026	Q1338A
	RM1-0036(T2,3)PU							
	RM1-0037(T2,3) Feed							

MODEL	P/U ROLLER	SEP PAD	FUSER	Maint. Kit	TRANSFER	P/U ASSY	Delivery Assembly	TONER
4240n / 4250	RL1-0019(T1) "D"	RL1-0007(T1)	RM1-1082	Q5421-67901	RM1-1110	RM1-0034(T1)	RM1-0026	Q5942A
	RM1-0036(T2,3)PU							Q5942X
	RM1-0037(T2,3) Feed							
4300	RL1-0019(T1) "D"	RL1-0007(T1)	RM1-0101E	Q2436-69007E	RM1-0699	RM1-0034(T1)	RM1-0026	Q1339A
	RM1-0036(T2,3)PU							
	RM1-0037(T2,3) Feed							
4345mfp	RL1-0019(T1) "D"	RL1-0007(T1)	RM1-1043	Q5998-67902	RM1-1110	RM1-1572	RM1-1047	Q5945A
	RM1-0036(T2,3)PU					PF2282K039NI ADF		
	RM1-0037(T2,3) Feed	PF2282K035NI ADF						
4350	RL1-0019(T1) "D"	RL1-0007(T1)	RM1-1082	Q5421-67901	RM1-1110	RM1-0034(T1)	RM1-0026	Q5942A
	RM1-0036(T2,3)PU							Q5942X
	RM1-0037(T2,3) Feed							
CLJ 4500, 4550	RB2-0744(T1)Bottom	RB2-0734 (T1)	RG5-5154E	N/A	RF5-2112		RG5-5135	C4191A(B)
	RB2-0717(T1)Top	RF5-1885 Feed/Sep	C4197A (KIT)		C4196A Kit			C4192A(C)
	RF5-2092(T2)				LZ185			C4193A(M)
	FB4-9817(500) "D"							C4194A(Y)
CLJ 4600	RG9-1529 (T1)	RF5-3750	C9725A (Kit)	N/A	Q3675A (Kit)	RG5-6468	N/A	C9720A(B)
	RF5-3739 (T2)							C9721A (Cyan)
								C9722A(Y)
								C9723A(M)
CLJ 4610 / 4650	RG9-1529 (T1)	RF5-3750	Q3676A (Kit)	N/A	Q3675A (Kit)	RG5-7453	N/A	C9720A(B)
	RF5-3739 (T2)							C9721A (Cyan)
								C9722A(Y)
								C9723A(M)
CLJ 4700 / 4730mfp	RL1-0019(T1) "D"		Q7502A (Kit)		Q7504A (Kit)	RM1-1756	RM1-1730	C5950A(B)
	RM1-0036(T2,3)PU		RM1-3131					C5951A (Cyan)
	RM1-0037(T2,3) Feed							C5952A(Y)
5000	RB2-1820(T1)	RF5-3439(T1)	RG5-5455E	C4110-69006E	RG5-3579	RG5-3519(T1)	RG5-3542	C4129X
	RB2-1821(T2)	RG9-1485(T2)				RG5-3521(T2)		
	FB4-9817 (T3-500) "D"					RF5-2636(500)		
	RF5-2634 (T3-500SHT)							

MODEL	P/U ROLLER	SEP PAD	FUSER	Maint. Kit	TRANSFER	P/U ASSY	Delivery Assembly	TONER
5100	RB2-1820(T1)	RF5-4119(T1)	RG5-7060E	Q1860-67902E	RG9-1542	RG5-3519(T1)	RG5-3542	C4129X
	RB2-1821(T2)	RF5-4120(T2)				RG5-3521(T2)		
5200	RL1-0915 (T1) P/U	RM1-2462 (T1)	RM1-2522		RM1-2485		RM1-2490 (FD)	Q7516A
	RM1-0731 (T2) P/U	RM1-2546 (T2) in Tray				RM1-2530 (T2)	RM1-2492 (FU)	
	RM1-0036 (T3) P/U							
	RM1-0037 (T3) Feed							
CLJ 5500	RF5-3340	RF5-3865(T1)	C9735A Kit	N/A	C9734A Kit	RG5-6670(T2)		C9730A(B)
	RG9-1529 (T1)	RF5-3338(T2)				RG5-6748(T3&4)		C9731A(C)
								C9732A(M)
								C9733A(Y)
CLJ 5550	RF5-3340	RF5-3865(T1)	Q3984-67901	N/A	C9734A Kit	RG5-7709(T2)		C9730A(B)
	RG9-1529 (T1)	RF5-3338(T2)				RG5-6748(T3&4)		C9731A(C)
								C9732A(M)
								C9733A(Y)
8000	RB1-6730(T1)	RF5-1455	RG5-4447E	C3971-69002E	RG5-1887	RG5-1800(T1)	RG5-1874E	C3909A
	RF5-1835(T2&3)	RF5-1834 Feed/Sep Roll				RG5-1852(PIU)		
8100 / 8150	RB1-9526(T1)	RF5-2703(T1)	RG5-4318E	C3914-69001E	RF9-1394	RG5-4330(T1)	RG5-1874E	C4182X
	RF5-2708(T2)	RF5-1834 Feed/Sep Roll				RG5-4334E (PIU)		
	RF5-1835(2000)							
CLJ 8500 / 8550	RB1-9526(T1)	RF5-1989	C4155A (Kit)	N/A	C4154A (Kit)	RG5-3054(T1)	RG0-0110	C4149A(B)
	RF5-1835(T2&3)	RF5-1834 Feed/Sep Roll	RG5-3060E			RG5-3132		C4150A(C)
								C4151A(M)
								C4152A(Y)
9000 / 9040 / 9050	RF5-3340(T2/3)	RF5-3338 Feed/Sep Roll	RG5-5750E	C9152-67901E	RF5-3319	RG5-5681 (T2/3)	RG5-5643 (FD)	C8543X
	RF5-3403 (T1)	RF5-3404 Sep Roll						
CLJ 9500	RB2-1820(T1)	RF5-3490	C8556A (KIT)	N/A	C8555A (Kit)	RG5-6090(T1)		C8550A(B)
	RF5-3338 x 3 (Sep)					RG5-6196		C8551A(C)
	RF5-3340 PU							C8552A(M)
								C8553A(Y)